

Features

- Utilizes a CREE XHP70 LED
- Driven by a dedicated IMR 18650 battery to emit up to 2,800 lumens brightness
- Ultra-bright dual-mode tactical blaze
- Dual-switch tail cap designed for tactical use and easy application
- Mode 1 Suppressing light: Quick access to turbo mode
- Mode 2 **STROBE READY™**: Quick access to Strobe Mode (Chinese Patent:201320545349.4)
- Four easily accessible brightness levels and memory function for fast boost
- Maximum beam intensity up to 21,000cd
- Extensive runtime up to 30 hours
- 289 meters far throw
- Integrated metal micro textured reflector for optimal peripheral illumination
- A power indicator LED hidden in the tail switch indicates battery power (Chinese patent: ZL201220057767.4)
- Electric reverse polarity protection
- Temperature regulation and protection
- Anti-rolling design
- Toughened ultra-clear mineral glass with anti-reflective coating
- Constructed from aero grade aluminum alloy
- Robust HAIII military grade hard-anodized
- Waterproof in accordance with IPX-8 (two meters submersible)

Dimensions

Length: 6.25" (159mm)
 Head Diameter: 1.57"(40mm)
 Tail Diameter: 1.18" (30mm)
 Weight: 7.52oz (213g)(without battery)

Accessories

1xNI18650D dedicated battery (for TM03 only), O-ring, spare tail cap cover, holster

Battery Type

The TM03 uses a dedicated Nitecore IMR 18650 Li-ion rechargeable battery for large current output.

Brightness & Runtime

FL1 STANDARD	HIGH	MID	LOW	LOWER
	2800 LUMENS	1350 LUMENS	550 LUMENS	40 LUMEN
	-	45min	2h15min	30h
	289m (Beam Distance)			
	21,000cd (Peak Beam Intensity)			
	1.5m (Impact Resistant)			
	IPX-8, 2m (Waterproof AND Submersible)			

NOTICE
 The above data has been measured in accordance with the international flashlight testing standards ANSI/NEMA FL1 using 1x Nitecore IMR18650(3.6V, 11.2Wh) battery under laboratory conditions. The data may vary slightly during real-world use due to battery type, individual usage habits and environmental factors.

Operating Instructions

Battery Installation

Install a dedicated IMR 18650D battery with the positive end pointing inward.

Note: The tail cap indicator LED will blink to indicate battery power upon battery installation. Please refer to Power Tips for details.

Tactical Momentary Illumination

Press and hold the tail switch to turn on the flash light, and release to turn it off.

On/Off Operation

To turn the TM03 on, press the tail switch until a "click" is heard.
 To turn the TM03 off, press the tail switch again until a "click" is heard.

Brightness Levels

With the TM03 turned on, press the MODE switch to cycle through power levels Low-Medium-High-Turbo. The TM03 has memory for brightness levels. When it is switched on, the TM03 will enter the brightness level last used.

Mode Selection

The TM03 has two special modes: the Suppressive Light mode and the **STROBE READY™** mode. To switch between these modes, follow the procedure below:

- Step 1:** With the TM03 turned off, take out the battery, and put inside again;
Step 2: Within 60 seconds, tighten the tail cap back on the TM03 while holding the MODE switch;
Step 3: Observe the flash upon tightening completion: one flash for Suppressive Light mode selected, and two flashes for **STROBE READY™** mode selected.
Note: Mode selection will be unavailable when battery voltage is below 3.7V.

Suppressive Light Mode

Quick access to turbo: In any setting of the TM03, including power-off, press and hold the MODE switch for over 0.2 second to access turbo brightness, and release to resume previous setting.

Quick access to strobe: In any setting of the TM03, including power-off, press the MODE switch twice in quick succession to access strobe mode, and press again to resume previous setting.

STROBE READY™ Mode

Quick access to strobe: In any setting of the TM03, including power-off, press and hold the MODE switch for over 0.2 second to access strobe mode, and release to resume previous setting.

Quick access to turbo: In any setting of the TM03, including power-off, press the MODE switch twice in quick succession to access turbo mode, and press again to resume previous setting.

Temperature Regulation and Protection

The TM03 features temperature regulation and protection. It automatically monitors its internal temperature in high and turbo levels. When its body temperature is higher than 50°C, the TM03 will automatically lower its brightness. When its body temperature drops below 50°C, the TM03 will gradually increase its brightness to high level.

Power Tips

Upon battery installation, the red power indicator LED in the tail switch will blink to indicate battery power:

1. Three blinks indicate power levels above 50%;
2. Two blinks indicate power levels below 50%;
3. One blink indicates power levels below 10%.

Changing Batteries

When the battery power is insufficient, the output appears to be dim or the flashlight becomes irresponsive. When the battery is close to depletion, the main LED will flicker until it completely goes off. In either condition, the battery should be replaced.

Precautions

1. Do not install a battery with polarity reversed. Otherwise the TM03 could not work.
2. Installing ordinary 18650 Li-ion batteries or other IMR 18650 batteries will compromise some functions of the TM03.
3. The standby time for the TM03 is approximately one year.
4. Do not direct beam into eyes as doing so can damage vision.
5. Keep small parts in the package away from children to avoid choking.
6. Do not dismantle, remodel or handle the TM03 in any improper way. Doing so will void your warranty.

Warranty Details


Our authorized dealers and distributors are responsible for warranty service. Should any problem covered under warranty occurs, customers can contact their dealers or distributors in regards to their warranty claims, as long as the product was purchased from an authorized dealer or distributor. NITECORE's Warranty is provided only for products purchased from an authorized source. This applies to all NITECORE products.

Any DOA / defective product can be exchanged for a replacement through a local distributor/dealer within the 15 days of purchase. After 15 days, all defective / malfunctioning NITECORE® products can be repaired free of charge for a period of 60 months (5 years) from the date of purchase. Beyond 60 months (5 years), a limited warranty applies, covering the cost of labor and maintenance, but not the cost of accessories or replacement parts.

The warranty is nullified if the product(s) is/are broken down, reconstructed and/or modified by unauthorized parties, or damaged by batteries leakage.

For the latest information on NITECORE® products and services, please contact a local NITECORE® distributor or send an email to service@nitecore.com.

※All images, text and statements specified herein this user manual are for reference purpose only. Should any discrepancy occurs between this manual and information specified on www.nitecore.com. Sysmax Industry Co., Ltd. reserves the rights to interpret and amend the content of this document at any time without prior notice.



SYSMAX ind.
 SYSMAX Industry Co., Ltd.
 TEL: +86-20-83862000
 FAX: +86-20-83882723
 E-mail: info@nitecore.com
 Web: www.nitecore.com
 Address: Rm1401-03, Glorious Tower, 850 East Dongfeng Road, Guangzhou, China 510600

Please find us on facebook:
 NITECORE Flashlights

